



1. Unpack and Inspect:

- Unpack the monitor and antenna, check for damage. The monitor has a combined data/power cable.

2. Mount Antenna:

- Install the antenna vertically on the generator's exterior, ensuring at least 20 cm separation from people.
- Use the drip loop to prevent water damage.

3. Install Monitor:

- Use magnetic feet to place the monitor on a stable surface, ideally horizontal.
- If mounted vertically, keep cables facing down.

4. Wiring:

- Refer to the wiring table on the next page for connection instructions.

5. Connect Antenna:

- Attach the antenna cable to the front of the monitor and hand-tighten.

6. Network Setup:

- Confirm LEDs lights are blinking. (Scan QR Code for light Sequence)
- Wait 15 minutes for network login, then call OmniMetrix to confirm.
- Access data via www.omnimetrix.net. Contact them for login help or training.



Kohler RDC2 Wiring Diagram			
SLEEVE COLOR	OMNI WIRE	FUNCTION	TERMINATION
Red	Red	Power In (9-30Vdc)	P1
	Black	Ground	0
Blue	Orange	Generator Run	70A
	Yellow/White	Remote Start	P21-3
	Brown/White	Remote Stop	P21-4

If you have any questions, please call OmniMetrix Tech Support at

770-209-0012 or email at techsupport@omnimetrix.net

